



### Portable Generator

Developed by:		Approved by:	Date created:	Last revision:
Jason M. Moffatt		G. Kaluzniak	January , 2016	December 1, 2022
Possible Hazards Present		Personal Protection Required		Additional Training
<ul style="list-style-type: none"> <li>- Inhalation of carbon monoxide</li> <li>- Fire/explosion</li> <li>- Burns</li> <li>- Electrocution</li> <li>- Slip/trip</li> </ul>		<ul style="list-style-type: none"> <li>- Steel Toed Boots</li> <li>- Safety Vest</li> <li>- Hard Hat</li> </ul>		- PPE
<ol style="list-style-type: none"> <li>1. Pull generator to well-ventilated work area.</li> <li>2. Ensure generator is fueled and inspect it before starting.</li> <li>3. Place cord out of way of workers walk path when possible</li> <li>4. If work area becomes wet, stop work with generator immediately.</li> <li>5. Ensure machine is turned off and unplugged when not in use.</li> </ol>				
<p><b>Documentation/Legislation</b>                  Workplace Safety and Health Regulation,                  M.R. 217/2006</p> <p>6 Personal Protective Equipment                  16 Machines, Tools and Robots                  4.1 Air Quality and Ventilation</p>			<p><b>This Safe Work Procedure will be reviewed anytime the task, equipment or materials change and at a minimum every three years.</b></p>	